

INVEREX SERIES

1000VA & 2000VA



Optional LED Panel



Features

- High Frequency Design
- Narrow / Wide Input Range Selection
- Build-in AC Charger
- Generator Compatible
- Optional LED / LCD Panel
- Cold Start Function
- Wall-Mount Compatible



I N V E R T E R

INVEREX SERIES



Model	Inverex 1000	Inverex 2000
Capacity	1000VA / 600W	2000VA / 1200W
Input		
Nominal Voltage	220 - 240 Vac	
Voltage Range	Wide mode: 100Vac - 280Vac Narrow mode: 190Vac - 260Vac	
Frequency	50Hz/60Hz (Auto Sensing)	
Output		
Nominal Voltage (Batt.mode)	220 - 240Vac	
Frequency (Batt.mode)	50Hz / 60Hz	
Waveform (Batt.mode)	Simulated Sinewave	
Transfer Time	15 - 20ms	
Battery		
Battery Voltage	12V	24V
Maximum AC Charge Current	10A	10A
Indicators		
Display	LED / LCD	
Alarm	Batt. Mode, Low battery, overload, fault, etc.	
Management		
Auto Recharge	Yes	
Auto Restart	Yes	
Power Management Software	Yes	
Physical		
Dimension(W x H x D)(mm)	250 x 90 x 265	
Net Weight (kg)	1.9	2.0
Environment		
Operating Humidity	0-90% non-condensing	
Operating Temperature	0 - 40°C	

* Specifications are subject to change without prior notice.

* Custom-made specifications are acceptable.



POWER LOGIC