

Product Name: Mixer Amplifier

Model No.: HY-M50



Features:

- Power output: 50W.
- Individual volume control for MIC and AUX input.
- Master volume control.
- Bass and treble control.
- 2 AUX inputs, 2 MIC inputs, 1 AUX output.
- MIC1 has priority(auto mute function).
- Clip, power, signal indicator
- 70V, 100V and 8 ohms output.
- Protections include power on(delay protection by relay), electronic protection for short-circuit.

Specification:

Model	HY-M50
Rated output	50W
Input power	AC220V/50Hz
Output	8Ω, 70V, 100V
S/N ratio	>75dB
Volume control	Bass±10dB at 100Hz Treble: ±10dB at 10KHz
Sensitivity	MIC1/2 /600Ω, 2.0mV(-54dB), unbalanced; AUX1/2 /10KΩ, 250mV(-10dB), unbalanced
Frequency response	20Hz~20KHz
Harmonic distortion	≤0.1% @1KHz
Working temperature	-20°C~+60°C
Working humidity	10%~90%
Power consumption	75W
Dimension	310*210*72mm
Weight	3.0Kg